Configuration for installing SunPower Drive as a simple plug&charge device.

On your mobile device or laptop, access the Wi-Fi connectivity settings and locate the SUNPOWER DRIVE network.

• No password is required to connect to the SUNPOWER DRIVE network.

Once connected to SUNPOWER DRIVE, launch your mobile browser (e.g. Google Chrome, Safari, etc.) and enter the IP address of the SunPower Drive exactly: **http://192.168.87.136:8080**

• This action will display the Web UI interface login page

• Log in with the following credentials:

Username: **xxcd**

Password: **28912891**

Scroll down to **Functions Enable.**

• Under **Card Type**, three options exist. By default, **Billing card** is selected.

• Select **Local PnC** and select **Submit**.

• Wait for the **Success!** Confirmation.

• Restart SunPower Drive by power cycling the charger at the dedicated charger MCB installed.

